

MODIFY POWER AND BAND G8

(A)

PMR HI/LOW (legal): SETTING FOR VERSION ONLY **PMR**

HIGH = 500 mW

LOW = 10 mW

(B)

PMR HI/LOW + LPD LOW (legal): SETTING FOR **PMR + LPD**

HIGH = 500 mW

LOW = 10 mW

(C)

LPD HI (legal): SETTING FOR VERSION ONLY **LPD**

HIGH = 10 mW

(D)

LPD HI (EXTENDED)

HIGH = 2 W

(E)

PMR HI/LOW + LPD HI/LOW (EXTENDED)

HIGH = 2W

LOW = 500 mW

LINK SETTING

J POWER 1 (JP1)	J POWER 2 (JP2)	J POWER 3 (JP3)	SETTING
0	0	0	D
0	0	1	C
0	1	0	A
0	1	1	B
1	0	0	A
1	0	1	A
1	1	0	E
1	1	1	A

0 = OPEN

1 = CLOSE

After editing mode to switch LPD turn on the radio, and then hold down the menu for 5 / 6 seconds until the display does not appear LPD channels. To return in PMR, repeat the procedure.

